

Servo Controlled Voltage Stabilizer

(Air Cooled 3 - 300 KVA)



Features & Benefits

- No potentiometer adjustments
- All parameters can be modified using the keypad in the front panel
- Set input voltage band
- Set output voltage
- Set output voltage sensitivity
- Output over / Under voltage cut-off
- Input over voltage / Under cut-off
- Over load cut-off
- Trip time delay adjustments with variable setting
- Manual and auto start facility
- Output start and stop facility

Technical Specification
Servo Controlled Voltage Stabilizer

Air Cooled 3 KVA - 300 KVA

Air Cooled Servo Control Voltage Stabilizer	
Capacity	3 - 300 KVA
Input Voltage Range *	A) Range 1: 295 V-465 V B) Range 2: 340 V-480 V C) Range 3: 360 V-460 V
Output Voltage Range *	380/400/415 V +/-1% Set
Input Frequency	47-53 Hz
Control Type	Digital-Micro controller based
Correction Speed*	16.6 to 70V / Sec
Reset	Manual / Auto Reset with time delay and programmable
Protections**	A) Electronic over & under voltage trip with time delay for input & output B) Electronic overload protection and short circuit protection upto 30 KVA through MCB and the manual bypass is built in. Above 30 KVA MCB /MCCB is Optional. C) Phase reversal protection and cut off D) Single phase prevention and cut off E) Neutral failure protection F) Frequency cut off protection G) Earth neutral voltage cut off protection
Metering Digital Type (Class 1 Accuracy with Full Scale ± 1)	A) Input phase to neutral B) Input phase to phase C) Output phase to neutral D) Output phase to phase E) Load Current in all the phases F) Frequency
Audio Alarm	For tripping conditions
Nature of Cooling	Natural air cooled upto 150 KVA & Forced air cooled above 150 KVA
Effect of Power Factor	Nil
Waveform Distortion	Nil
Annunciation Panel	Non Latching LED indications with dual colour for Over load Latching Conditions
Efficiency	> 95 to 98% (Based on the Capacity)
Cabinet Colour	Dark Grey RAL 7016
Provision of Cabling	Input and Output terminations with provisions for fixing cable glands
Servo Motor Drive	Rugged AC step synchronous motor
Operating Temperature	0-45°C
Related Standard	IS 9815
Degree of Protection	IP 20
Display	LED, LCD (Optional)
Application	Indoor / Floor Mount

* Range can be customised to customer requirement

◆ All specifications are subject to change

◆ Custom models available on request

**Above 30KVA is an Optional

Fuji Electric Consul Neowatt Pvt. Ltd.

(CIN:U31900TN1985PTCO11866)

 119, 120, 120A, Electrical and Electronics Industrial Estate,
 Perungudi, Chennai - 600 096, Tamil Nadu, India

☎ +91 78100 09955

✉ enquiry@consulneowatt.com

🌐 www.india.fujielectric.com